



Z.I. da Poupa II, Rua A - Fracção C, 4780-793 Santo Tirso
 Tel./ Fax: 252856106 * Telem: 912255637
 geral@interfire.pt
 www.interfire.pt

AUTO CHARGE 40/20

- Charge Single Battery Bank at 40 Amps
- Power Auxiliary Loads with 20 Amp 'Battery Saver'
- Remote Display Included



Features

- 60A total: 40A battery charger, 20A battery saver
- Automatic operation regulates output to a single battery bank
- Separate 20 Amp ATC fuse protected "Battery Saver" output eliminates drain on vehicle battery when in station
 - Clean output poses no interference with radios and other mobile devices
- Battery Type Selector Switch: Lead-Acid/AGM or Gel-Cell
- 1-hour "boost" voltage for rapid recovery
- Automatic current limit
- Reverse polarity protected
- AC input circuit breaker protection



Remote Display Options

 Bar Graph Display 091-199-001	 Status Center Display 091-194-IND	 Status Center Display in Watertight Case 091-194-IND-WT-XX	Color Options <table border="0"> <tr> <td> YW</td> <td> RD</td> </tr> <tr> <td>Yellow</td> <td>Red</td> </tr> <tr> <td> WH</td> <td> GY</td> </tr> <tr> <td>White</td> <td>Gray</td> </tr> <tr> <td> BL</td> <td> BLK</td> </tr> <tr> <td>Blue</td> <td>Black</td> </tr> </table>	 YW	 RD	Yellow	Red	 WH	 GY	White	Gray	 BL	 BLK	Blue	Black
 YW	 RD														
Yellow	Red														
 WH	 GY														
White	Gray														
 BL	 BLK														
Blue	Black														

Part Number	Description	Electrical Data				Dimensions			Wt.
		DC Volts	DC Amps	AC Volts	AC Amps	L	W	H	
091-216-40/20	Auto Charge 40/20, Bar Graph Display	12	40 / 20	120	8.5	13.25"	7.13"	5.25"	13
091-216-40/20-194	Auto Charge 40/20, Status Center	12	40 / 20	120	8.5	13.25"	7.13"	5.25"	13
091-216-40/20-194-WT-XX	Auto Charge 40/20, Watertight Display	12	40 / 20	120	8.5	13.25"	7.13"	5.25"	13